

Analog input 560AIR01

RTU560 product line



Analog input, 8 channels

- AD converter resolution: 16 bit
- Measuring ranges: ± 2 mA; ± 5 mA; ± 10 mA; ± 20 mA; ± 40 mA; ± 2 V DC; ± 20 V DC

Application

The 560AIR01 is a module of the RTU560 product line and records up to 8 analog measured values.

The module 560AIR01 is able to process the following types of signals:

- Analog measured values (AMI)
- Measured floating point information (MFI)

Following measurement ranges can be configured:

- ± 2 mA
- ± 5 mA
- ± 10 mA
- ± 20 mA
- ± 40 mA
- ± 2 V DC
- ± 20 V DC

Other input ranges and live zero values are generated from these values by conversion on the communication unit (CMU).

Characteristics

Analog inputs

Basic signal checks and cyclic processing functions are already be done locally in order to unburden the

communication unit. The module transmits relevant changes as event via the RTU I/O bus.

The 8 differential inputs are galvanically connected to the power supply.

Single-ended or differential input values are resolved by up to 4096 steps (12 bit plus sign) for 100 % measurement amplitude.

The differential inputs are protected against static and dynamic over-voltages by a protection circuit. A low-pass filter suppresses unwanted frequency components.

The internal high resolution of the AD converter allows to scan all measuring ranges with the same resolution. An additional measurement channel is used for automatic zero calibration. This compensates the longterm drift of the components.

For elimination of tolerances a calibration is done during production.

Measuring range and line frequency are easily to configure by the RTUtil500 configuration tool. The synchronization of the scan cycle with the line frequency is used to increase the line frequency interference suppression of the DC input signal.

Frequency	Conversion time per channel	Scan cycle time (same for all channels)
60 Hz	54 ms	486 ms
50 Hz	54 ms	486 ms
16.7 Hz	155 ms	1395 ms

Power supply input

The required power for the module is supplied via the RTU560 backplane.

I/O controller (IOC)

The micro-controller (MPU) on the module processes all time critical I/O tasks of the parameterized processing functions. Moreover it carries out the interactive communication with the I/O bus. All configuration data and processing parameters are loaded by the communication unit via the RTU560 I/O bus.

The module is equipped with a serial interface to the RTU560 I/O bus on the backplane.

The analog input unit can execute the following processing functions on the measured values:

- Scan cycle and line frequency interference suppression
- Zero value supervision and switching detection
- Smoothing
- Threshold value monitoring on absolute value or with accumulation
- Periodic transmission and background cycles

The module provides a data buffer for temporally storing of up to 50 event messages including time stamps. The events are stored in chronological order designated for transmission to the communication unit (CMU).

During initialization and operation the module executes a number of tests. If a fault occurs it is reported to the communication unit. All fault conditions impairing the function of the module are displayed as a common fault signal by a red LED. A failure of the connected module(s) is detected and signalized by the communication unit.

Technical data

In addition to the RTU500 series general technical data, the following applies:

Analog input channels 560AIR01	
Inputs	8 differential inputs
Configurable measuring range	<ul style="list-style-type: none">• ± 2 mA• ± 5 mA• ± 10 mA• ± 20 mA• ± 40 mA• ± 2 V DC• ± 20 V DC
Input impedance	150 Ω @ ± 2 mA and 5 mA
	50 Ω @ ± 10 to ± 40 mA
	110 k Ω @ ± 2 and ± 20 V DC
Max. load	80 mA continuous @ ± 10 to ± 40 mA
	40 mA continuous @ ± 2 and ± 5 mA
	38 V/ 0.5 mA @ ± 2 and ± 20 V DC
Resolution	12 bit + sign
	11 bit + sign @ ± 2 V DC
AD converter resolution	16 bit
Accuracy at 25 °C	≤ 0.1 %
	≤ 0.2 % @ ± 2 V DC
Linearity error at 25 °C	≤ 0.1 %
Temperature drift	≤ 100 ppm/K (0... 70 °C)
Max. common mode input voltage	± 150 V DC (electrical limit)
	± 8 V DC (functional limit)
Max. differential input voltage	± 4 V DC (current input)
	± 38 V DC (voltage input)
Common mode rejection	> 70 dB @ 25 °C
	> 60 dB @ 0... 25 °C
Configurable line frequency f_N	<ul style="list-style-type: none">• 16.7 Hz• 50 Hz• 60 Hz
	> 100 dB @ $f_N \pm 2$ %
	> 45 dB @ $f_N \pm 10$ %

Current consumption for power supplied via RTU560 backplane

5 V DC	75 mA
24 V DC	--

Signaling by LEDs

ERR (red)	Common fault information for the module
-----------	---

Mechanical layout

Dimensions	160 mm x 100 mm, 3HE euro card format 4R (20 mm) front panel
Housing type	Printed circuit board
Mounting	for mounting in RTU560 racks
Weight	0.3 kg

Connection type

RTU560 backplane connector	48 pole type F DIN 41612
----------------------------	--------------------------

Immunity test

Electrostatic discharge IEC 61000-4-2	8 kV air / 6 kV contact (level 3)
	Performance criteria A
Electrical fast transient / Burst IEC 61000-4-4	2 kV (level 3)
	Performance criteria A
Surge IEC 61000-4-5	2 kV (level 3)
	Performance criteria A

Environmental conditions - climatic

Operating temperature EN 60068-2-14	-25 °C ... 70 °C
Start up EN 60068-2-1	-40 °C
Max. operating temperature, +85 °C max. 96h EN 60068-2-2	
Relative humidity EN 60068-2-30	5 ... 95 % (non condensing)

Ordering information

560AIR01 R0001	1KGT036500R0001
----------------	-----------------

